

Protege Half DIN Rail 16 Input Expander

The Protege Half DIN Rail 16 Input Expander provides an additional 16 inputs to the Protege system, an advanced technology security product providing seamless and powerful integration of access, security and building automation. The Input Expander provides extensive hardware advancements that allow flexible input programming and configuration, and is designed for use with industry-standard DIN rail mounting.



Feature Highlights

- > Expands the Protege system by 16 inputs
- > Connects any combination of normally closed or normally open inputs, configurable per input
- > Compact two-tier half DIN rail module design
- > Utilizes analog to digital processing with 5x over sampling
- > 4 state input alarm using resistors to provide short, alarm, closed and tamper conditions
- > High performance 32 Bit processor
- > Secure encrypted RS-485 module communications
- > Online and remote upgradable firmware
- > Designed for use with industry-standard DIN rail mounting

Power Supply

Device power is supplied from a 12VDC input. Ultra low current requirements ensure cost effective power distribution.

Small Footprint

The compact two-tier half DIN Rail module design takes up less valuable real estate to provide more control in less space

Communication

Single RS-485 communication interface port used for all network communication functions and interconnection to other modules.

Upgradable Firmware

Utilizing the latest flash technology and high performance communication mediums, the

firmware can be updated using the Loadit utility over the system module network.

Connectivity and System Expansion

Expanding the Protege System with local inputs from the Input Expander allows convenient cost effective expansion up to:

- > 16 inputs can be assigned to any 4 areas in the system each being processed using different options or features
- > Address configuration of the Input Expander interface is achieved using the address programming feature of the Protege System Controller

Technical Specifications

Power Supply	
DC Input Voltage	11-14VDC
DC Output Voltage (DC IN Pass-Through)	10.83-14.0VDC 0.7A (Typical) Electronic Shutdown at 1.1A
Operating Current	80mA (Typical)
Total Combined Current*	3A (Max)
Low Voltage Cutout	8.7VDC
Low Voltage Restore	10.5VDC
Communication	
RS-485	Module Network
Inputs	
Zone Inputs	16 High Security Monitored Inputs(10ms to 1hr Input Speed Programmable)
Trouble Inputs	16
Dimensions	
Dimensions (L x W x H)	78 x 90 x 60mm (3.07 x 3.54 x 2.36")
Weight	238g (8.4oz)
Temperature	
Operating	0°-50°C (32° - 122°F)
Storage	-10°- 85°C (14° - 185°F)
Humidity	0%-93% non-condensing, indoor use only (relative humidity)

* The Total Combined Current refers to the current that will be drawn from the external power supply to supply the Input Expander and any devices connected to the Expander's outputs. The Auxiliary outputs are directly connected via electronic fuses to the N+ N- input terminals, and the maximum current is governed by the trip level of these fuses.

Disclaimer: Whilst every effort has been made to ensure accuracy in the representation of this product, neither Integrated Control Technology Ltd nor its employees, shall be liable under any circumstances to any party in respect of decisions or actions they may make as a result of using this information. In accordance with the Integrated Control Technology policy of enhanced development, design and specifications are subject to change without notice.

ICTeSecurity.